



3 Channel I/O Unit мюз24



MIO324 3 channel I/O unit

Overview

An extensive range of interfaces are available to support the Menvier range of control panels, providing solutions for most design requirements.

The MIO324 3 channel I/O unit enables simple interfacing between the fire system and other equipment such as nurse call systems or access control systems. The inputs are fully monitored for open and short circuits.

Features

- Quick and simple to install
- Soft addressed
- 3 separate inputs and 3 separate outputs
- Inputs monitored for open and short circuits
- Integral short circuit isolator


Benefits

- Plug and play no hard addressing required
- Built in short circuit isolator no additional hardware required
- Unit takes 3 inputs, 3 outputs

 only 1 address required to monitor and control saving on equipment and installation



Dimensions



(mm)	W (mm)	D (mm)
88	147	60


Technical Specification

Code	MIO324	
Description	3 channel I/O unit	
Standards	EN54 Pt17 & Pt18 2005	
Specification		
Operating Voltage	18V dc to 30V dc	
Quiescent Current	310µA	
Maximum Switching Voltage	50V ac or 30V dc	
Output Relay Contact Rating	1A at 30V resistive, 0.5A inductive	
Environmental		
Operating Temperature	-10°C to +60°C	
Humidity (non condensing)	0 to 95% RH	
Physical		
Construction	PC/ABS	
Dimensions (H x W x D)	88mm x 147mm x 60mm	
Weight	0.23kg	
Ingress Protection	IP40	
Compatibility		
Suitable for use with	Menvier intelligent addressable fire systems	

Installation

- 1.3 Channel input output unit is fixed to a deep
- double gang back box (supplied). 2. All connections are via heavy duty terminals.
- Cable entry can be top, bottom, side or rear.
- 4. Can be surface or semi recessed mounted.
- 5. Relay contacts are rated at 24V dc 1A.

Standard Connections



NOTES:

- 1. Earth (Screen) cable must be connected to its adjacent earth terminal.
- 2. The end of line resistor must always be fitted, even if input is not used.
- 3. Input circuit is monitored for wiring open and short circuit.
- 4. Output relay is a set of changeover volt free-contacts and is not monitored.

Product Codes

Code	Description
MIO324	3 channel I/O unit
MIO324S	3 channel I/O unit, resets on silence
MIO324T	3 channel I/O unit, contains 3 separate addresses

Cooper Lighting and Safety Ltd, Wheatley Hall Road, Doncaster, South Yorkshire, DN2 4NB. UK. T: +44 (0) 1302 303350 | F: +44 (0) 1302 303332 | E: techsupport@cooperfire.com | W: www.cooperfire.com